

## Lightway Industries

### INSTALLATION OPERATION INSTRUCTIONS

**WARNING** – Before starting the installation, disconnect the power by turning off the circuit

Turning the power off using the light switch is not sufficient

1. If you are replacing an existing fixture, disconnect and remove the old fixture. Expose the supply wiring from the outlet box.
2. Raise the fixture back chassis plate(A) to the wire box. Mark desired mounting location. lower back chassis plate(A) and pre-drill mounting holes. Insert wall anchors (Supplied By Others)..
3. Raise fixture back chassis plate(A) to mounting location and run supply wires through back plate. Mount the fixture back chassis plate(A) to the wall using screws supplied with wall anchors (Supplied By Others)..
4. Make electrical connections: Connect grounding wire (green or bare copper) from the supply circuit to the green colored wire from the fixture. Connect the white wire(s) from the fixture to the white wire of the supply circuit. Connect the black wire(s) from the fixture to the black or supply wire of the supply circuit. Use UL Listed wire connectors (by others). Secure wire connectors with UL Listed electrical tape (by others).
5. Place the cover(B) onto the fixture back chassis(A) plate. Insuring that all wires are free and not pinched. remove protective film from Cover (B).
6. Install and tighten (2) 8–32 screws (C) (provided) for cover as shown in figure.
7. Install lamps (by others) do not exceed recommended wattage.
9. Install lens (D) and end caps (E) (2) and tighten (2) 8–32 Knobs(F) (provided) as shown in figure.
10. Restore power.

