

Lightway Industries

INSTALLATION OPERATION INSTRUCTIONS

WARNING – Before starting the installation, disconnect the power by turning off the circuit breaker or removing fuse. Turning the power off using the light switch is not sufficient to prevent electrical shock.

1. If you are replacing an existing fixture, disconnect and remove the old fixture. Expose the supply wiring from the outlet box.
2. Raise the housing to the wire box. Mark desired mounting location. lower fixture. pre drill mounting holes. Insert wall anchors (Supplied By Others).
3. Raise fixture to mounting location and run supply wires into housing. Mount the fixture housing to the wall.
4. Make electrical connections: Connect grounding wire (green or bare copper) from the supply circuit to the green colored wire from the fixture. Connect the white wire(s) from the fixture to the white wire of the supply circuit. Connect the black wire(s) from the fixture to the black wire of the supply circuit. Use UL Listed wire connectors (by others). Secure wire connectors with UL Listed electrical tape (by others).
5. Place the chassis housing into the fixture housing. Insuring that all wires are free and not pinched.
6. Install and tighten (4) 8–32 screw (provided) for chassis housing as shown in figure.
7. Install the fixture lamp (by others) do not exceed recommended wattage.
8. Install Tempered glass cover tighten (2) 8–32 screw (provided) as shown in figure.

IMPORTANT: In order to comply with established electrical code, the installer must seal the area around the fixture base and the wall, with caulking compound such as GE 100% or Dow Corning 100% silicone to provide a watertight seal in accordance with the differing surface textures of the wall.

